Evaluation and Investigation of Okumura Cost 231 Hata and SUI Models for WiMAX Network in Suburban and Rural Areas

Ву

SLAH ABDULSLAM MOHAME MAGHAWRI



A Project Paper Submitted in Partial Fulfillment as the Requirements for the Master in Information Technology by Coursework in Faculty of Creative Media Innovative Technology

IUKL

2017

Abstract of project paper presented to the senate of Infrastructure University Kuala Lumpur in partial fulfilment of the requirement degree of Master in Information Technology.

EVALUATION AND INESTIGATION OF OKUMURA, COST 231 HATA AND SUI MODELS FOR WIMAX NETWORK IN SUBURBAN AND RURAL AREAS

By

SLAH ABDULSLAM MOHAME MAGHAWRI February /2017

Chair: Nasarudin Bin Daud

Faculty: Faculty of Creative Media Innovative Technology

Nowadays the demand for broadband Internet connections is growing. At the same time, ADSL-type accesses are increasing, but these technologies have limitations on bit rates and range, and do not allow for the flexibility of a wireless connection. In recent years, WiFi has revolutionized networks but we are already talking about a new technology: WiMAX, which is based on IEEE 802.16x standards. The main objective of our work is to calculate the path loss for the models: COST 231 Wi, ECC 33 (Okumura extended), COST 231 HATA and SUI, for a fixed WiMAX network. As well as we compared these models in term of path loss. Thus we have implemented a path loss simulation tool for a WiMAX network, which has as input radio transmission parameters, such as transmission frequency, height of the antennas and the distance. And as output the path loss values as well as the path loss graph for the different models, in rural and suburban areas. Thus we vary of the radio transmission parameters in order to determine the best possible values for antenna height for both transmitter and receiver as well as the best values for operating frequency. And finally we compared the models: COST 231 Wi, ECC 33 (Okumura extended), COST 231 HATA and SUI, in rural and suburban areas

ACKNOWLEDGEMENTS

No one walks alone on the journey of life. I do not know from where to start thanking those people who helped me, walked with me along the way on writing this project.

First of all I would like to thank the Almighty Allah for his blessing and giving me the strength to perform the project and massive thank to my father, mother and my wife who have been always supporting me and courage me with the words that get me back and focused on achieving my goals in life.

I also would like to thank my supervisor: Nasarudin Bin Daud for helping me and being there for me whenever I needed his supervision. No words that is express the kindness, trust and treatment that he has shown to us and a billion thanks are not enough for him. As well as my project examiner Dr.Abudhahir Buhari for his useful corrections and comments.

Now I would like to highlight to thank the people who have walked me through many subjects. My friend **Milud Moftah Daw** and to all the people that, this project would no have been possible without their support. THANK YOU.

APPROVAL

This thesis was submitted to the Senate of Infrastructure University Kuala Lumpur (IUKL) and has been accepted as partial fulfilment of the requirement for the degree of (Master in Information Technology).

The members of the thesis Examination Committee ware as follow:

Name of Supervisor: Mr.Nasarudin Bin Daud

Senior Lecturer

Name of Faculty: Faculty of Creative Media Innovative Technology

Infrastructure University Kuala Lumpur (IUKL)

JKL) Department of Networking
Faculty of Creative Media & Innovative Technology
Infrastructure University Kuala Lumpur
Tel: 603-8738 33

Name of Examiner: Dr. Abudhahir Buhari

Senior Lecturer

Name of Faculty: Faculty of Creative Media Innovative Technology Infrastructure University Kuala Lumpur (IUKL)

Dr. Abudhahir Buhari

Lecturer
Faculty of Creative Media & Innovative Technolog
Infrastructure University Kuala Lumpur (TUKL)

Assoc. Prof. Dr Manal Mohsen Abood
Director
Centre for Postgraduate Studies
Infrastructure University Kuala Lumpur (IUKL)

The state of the s

Assoc. Prof. Dr. Manal Mohsen Abood, PhD Director Centre for Postgraduate Studies

Infrastructure University Kuala Lumpur (IUKL)

Date: 4/5/17

Dr. Abudhanir Buhami

DECLARATION

I declare that the project is my original work except for quotations, citations and which have been duly, acknowledge. I also declare that it has not been previously and is not concurrently submitted for any other degree at Infrastructure University Kuala Lumpur or any other institutions.

Signature:

Name: SLAH ABDULSLAM MOHAMED MAGHAWRI

Date ...04.105/2017

TABLE OF CONTENTS ABSTRACT ACKNOWLEDGEMENTS APPROVAL DECLARATION LIST OF TABLES LIST OF FIGURES LIST OF ABBREVIATION		Page ii iii iv v ix x		
CHAPTE			1	
	ODUCI			
1.1	Overv	Overview		
1.2	Resear	Research Background		
1.3	Proble	Problem Statement		
1.4	Object	Objectives		
1.5	Scope	Scope of Project		
1.6	Outlin	Outline of Project		
2 LITE 2.1	ERATUI Introd	RE REVIEW uction	6	
2.2	WiMA	AX	6	
	2.2.1	Overview of WiMAX	7	
		Presentation of the access architecture for WiMAX	8	
	2.2.3	Several application schemes	9	
	2.2.4	Constraints related to the deployment of WiMAX	9	
	2.2.5	The frequency band	10	
	2.2.6	The IEEE 802.16 Standard	11	
2.3		gation models	13	
2.4		gation effects	13	
۷.٦	-			
	2.4.1	Attenuation	14	
	2.4.2	Fading	14	
	2.4.3	Interference	15	
	2.4.4	Multipath	15	

			2.4.4.1	Reflection	15
			2.4.4.2	Diffraction	15
			2.4.4.3	Scattering	16
			2.4.4.4	Refraction	16
	2.5	Outdo	or Propag	gation Models	17
		2.5.1	Empirio	eal	17
		2.5.2	Determ	inistic	17
		2.5.3	Stochas	tic	17
	2.6	The pr	opagatio	n channel	18
	2.7	Propag	gation in	a real environment	18
	2.8	Path lo	oss with p	propagation models	19
	2.9	Types	of propa	gation models	19
		2.9.1	The Fre	e space propagation model	20
		2.9.2	Okumu	ra-Hata Model	21
		2.9.3	Hata-Ol	kumura extended model or ECC-33 Model	23
		2.9.4	Erceg n	nodel (SUI model)	23
		2.9.5	COST 2	231 Hata Model	25
		2.9.6	Hata M	odel	26
		2.9.7	COST2	31Walfisch-Ikegami Model	26
	2.10	Frequ	aency Co	rrection and Receiver Antenna Heights	29
	2.11	Com	parison		29
	2.12	Conc	lusion		30
3	METH	HODO	LOGY		31
	3.1	Intro	duction		31
	3.2	Wate	erfall dev	elopment model	31
	3.3	Why	did we c	hoose Waterfall model	32
	3.4	Appl	ying Wat	terfall model to develop our system	33
		3.4.1	Require	ements analysis:	33

)	3.4.1.1 Hardware requirement	33
		X g	3.4.1.2 Software requirement	33
		3.4.2	Design	34
		3.4.3	Implementation and coding	35
		3.4.4	System Testing	35
		3.4.5	Results analysis	36
	3.5	Path lo	oss calculation	37
	3.6	Concl	usion	37
4	RESUI	LTS AN	ND ANALYSIS	38
	4.1	Introd	uction	38
	4.2	Simul	ation tool	38
	4.3	Calcu	lation of path losses	38
	4.4	Simul	ation parameters	34
		4.4.1	Determining the best antenna height for transmitter	40
		4.4.2	Determining the best antenna height for receiver	42
		4.4.3	Determining the best values for operating frequency	43
		4.4.4	Effect of the distance between transmitter and receptor	45
	4.5	Path 1	on path loss ost models comparison	45 45
	4.6	Concl	usion	47
5	CONC	LUSIO	NS	48
	5.1	Concl	usion	48
	5.2	Objec	tives fulfillment	49
RI	EFEREN	CES		50
Appendix-A MATLAB Code for Suburban and rural environment in different antenna heights 54			54	

LIST OF TABLES

Table 2.1:	Validity parameters of the Hata-Okumura model	23
Table 2.2:	Values of parameters according to the type of terrain	24
Table 2.3:	Compare between Types of propagation models	29
Table 3.1:	Parameters	34
Table 4.1:	Variable simulation parameters	39
Table 4.2:	Shows fixed simulation parameters	40
	The impact of the transmitter height on the path loss in sub urban area	40
Table 4.4:	The impact of the transmitter height on the path loss in rural area	40
Table 4.5:	The impact of the receiver height on the path loss in sub urban area	42
Table 4.6:	The impact of the receiver height on the path loss in rural area	42
	The impact of the operating frequency on the path loss in sub urban area	44
	The impact of the operating frequency on the path loss in rural area	44
Table 4.9:	The best values for simulation parameters	45

LIST OF FIGURES

Figure 1.1:	Principle of operation of the WiMAX	2
	Evolution of the modulation format as a function of distance or attenuation WiMAX Access Network Architecture	8
Figure 2.3:	The frequency band	11
Figure 2.4:	Scattering of a wave	16
Figure 2.5:	Types of propagation effects	18
Figure 2.6:	Free space attenuation	20
Figure 2.7:	Free space propagation	34
Figure 3.1:	Waterfall model's steps.	37
Figure 3.2:	Step 1 of flow diagram	38
Figure 3.3:	Step 2 of flow diagram	39
Figure 4.1:	Path Loss Calculator Interface	39
	Path Loss with transmitter antenna height = 30m in sub urban area Path Loss with transmitter antenna height = 30m in rural area	41 41
Figure 4.4:	Path Loss with receiver antenna height = 10m in sub urban area	43
Figure 4.5:	Path Loss with receiver antenna height = 10m in rural area	43
Figure 4.6:	Path Loss with operating frequency = 3.5m in sub urban area	44
Figure 4.7:	Path Loss with operating frequency = 3.5m in rural area	45
Figure 4.8:	Path Loss with the best values of the parameters in rural areas	46
Figure 4.9:	Path Loss with the best values of the parameters in sub urban area	47

LIST OF ABBREVIATION

Abbreviation	Meaning
BS	Base Station
ECC	Electronic Communication Committee
FDD	Frequency Division Duplex
FSL	Free Space Loss
GIS	Graphical Information System
GSM	Global System for Mobile Communications
ITU	International Telecommunication Union
LOS	Line-of-Sight
MANs	Metropolitan Area Networks
MAC	Medium Access Control
MMDS	Multipoint Microwave Distribution System
NLOS	Non-Line-of-Sight
OFDM	Orthogonal Frequency Division Multiplex
OFDMA	Orthogonal Frequency Division Multiple Access
PL	Path Loss
et al.	(et alia); and others

CHAPTER 1

INTRODUCTION

1.1 Overview

During last decade, the evolution of wireless networks and broadband technologies has captured the imagination and invention of industrialists around the world. Among the different technologies is WIMAX, which is based on IEEE 802.16x standards. This technology is characterized by high-speed data transmissions over the air. In addition, these features will help telecom operators to improve the quality of transmission. Planning is a very important phase for network deployment. Indeed, it is used to predict the necessary resources (equipment, frequency, and bandwidth) to serve a set of subscribers. It also allows managing the quality of transmission, by using path loss models.

In this study, we will put side by side and inspect few path loss models (Okumura Model, Cost-231Hata Propagation Model, and Stanford University Interim (SUI) model) for sub-urban and rural cases using WIMAX networks.

1.2 Research Background

The name "WiMAX" was created by the WiMAX Forum, which was formed in June 2001 to promote conformity and interoperability of the standard, including the definition of predefined system profiles for commercial vendors. The forum describes WiMAX as "a standards-based technology enabling the delivery of last mile wireless

broadband access as an alternative to cable and DSL". IEEE 802.16m or WirelessMAN-Advanced is a candidate for the 4G, in competition with the LTE Advanced standard. WiMAX refers to interoperable implementations of the IEEE 802.16 family of wireless-networks standards ratified by the WiMAX Forum. (Similarly, Wi-Fi refers to interoperable implementations of the IEEE 802.11

REFERENCES

Abdul Khaleque, (7, March 2017) Wi Max Updated. URL:https://www.slideshare.net/akhaleque/wi-max-updated-presentation.

Abhayawardhana, V. S., I. J. Wassell, D. Crosby, M. P. Sellars, and M. G. Brown. 2005. "Comparison of Empirical Propagation Path Loss Models for Fixed Wireless Access Systems." In 2005 IEEE 61st Vehicular Technology Conference, 1:73–77 Vol. 1. doi:10.1109/VETECS.(2005).1543252.

Bertoni, Henry L. (1999). Radio Propagation for Modern Wireless Systems. Pearson Education.

Caso, Giuseppe, et al. "ViFi: Virtual Fingerprinting WiFi-based Indoor Positioning via Multi-Wall Multi-Floor Propagation Model." arXiv preprint arXiv:1611.09335 (2016).

Cuiñas, I., J. A. Gay-Fernandez, A. V. Alejos, and M. G. Sánchez. (2010). "A Comparison of Radioelectric Propagation in Mature Forests at Wireless Network Frequency Bands." In Proceedings of the Fourth European Conference on Antennas and Propagation, 1–5.

Dinnebier, Robert E. (2008). Powder Diffraction: Theory and Practice. Royal Society of Chemistry.

Ekka, Ashish. (2012.) "Pathloss Determination Using Okumura-Hata Model for Rourkela." BTech. http://ethesis.nitrkl.ac.in/3774/.

Erceg V, L. J. Greenstein, S. Y. Tjandra, S. R. Parkoff, A. Gupta, B. Kulic, A. A. Julius, and R. Bianchi, "An empirically based path loss model for wireless channels in suburban environments" IEEE J. Select. Areas Commun., vol. 17, pp. 1205–1211, July 1999.

Genc, V., S. Murphy, Y. Yu, and J. Murphy. (2008). "IEEE 802.16J Relay-Based Wireless Access Networks: An Overview." IEEE Wireless Communications 15 (5): 56–63. doi:10.1109/MWC.2008.4653133.

Gesbert, D., M. Shafi, Da-shan Shiu, P. J. Smith, and A. Naguib. (2003). "From Theory to Practice: An Overview of MIMO Space-Time Coded Wireless Systems." IEEE Journal on Selected Areas in Communications 21 (3): 281–302. doi:10.1109/JSAC.2003.809458.

Ghasemi, Abdollah, Ali Abedi, and Farshid Ghasemi. (2012). "Terrestrial Mobile Radio Propagation." In Propagation Engineering in Wireless Communications, 215–87. Springer New York. http://link.springer.com/chapter/10.1007/978-1-4614-1077-56.

Goldsmith, Andrea. (2005). Wireless Communications. Cambridge University Press.

Hoymann, Christian. (2005). "Analysis and Performance Evaluation of the OFDM-Based Metropolitan Area Network IEEE 802.16." Computer Networks, Selected

Papers from the European Wireless (2004) ConferenceEuropean Wireless 2004, 49 (3): 341–63. doi:10.1016/j.comnet.2005.05.008.

Jensen, M. A., and J. W. Wallace. (2004). "A Review of Antennas and Propagation for MIMO Wireless Communications." IEEE Transactions on Antennas and Propagation 52 (11): 2810–24. doi:10.1109/TAP.2004.835272.

Jung, P., and B. Steiner. (1995). "A Joint Detection CDMA Mobile Radio System Concept Developed within COST 231." In 1995 IEEE 45th Vehicular Technology Conference. Countdown to the Wireless Twenty-First Century, 1:469–73 vol.1. doi:10.1109/VETEC.1995.504911.

Kumar, Amitabh. Mobile broadcasting with WiMAX: principles, technology, and applications. CRC Press, (2014).

Li, Bo, et al. "A survey on mobile WiMAX [wireless broadband access]." IEEE Communications magazine 45.12 (2007): 70-75.

Li, Q., G. Li, W. Lee, M. i Lee, D. Mazzarese, B. Clerckx, and Z. Li. (2010). "MIMO Techniques in WiMAX and LTE: A Feature Overview." IEEE Communications Magazine 48 (5): 86–92. doi:10.1109/MCOM.2010.5458368.

Lima, A. G. M., and L. F. Menezes. (2005). "Motley-Keenan Model Adjusted to the Thickness of the Wall." In SBMO/IEEE MTT-S International Conference on Microwave and Optoelectronics, 2005., 180–82. doi:10.1109/IMOC.2005.1580040.

Lowery, Arthur James, and Jean Armstrong. (2006). "Orthogonal-Frequency-Division Multiplexing for Dispersion Compensation of Long-Haul Optical Systems." Optics Express 14 (6): 2079–84. doi:10.1364/OE.14.002079.

Md Didarul Islam and Younas, O. and F. Banat,. "Performance assessment of a multi-stage solar still coupled with Fresnel lens for water desalination." Therm. Energy Power Eng. 2.4 (2013): 164-170.

Medeisis, Arturas, and Algimantas Kajackas. "On the use of the universal Okumura-Hata propagation prediction model in rural areas." Vehicular Technology Conference Proceedings, (2000). VTC 2000-Spring Tokyo. 2000 IEEE 51st. Vol. 3. IEEE, 2000.

Meng, Yu Song, Yee Hui Lee, and Boon Chong Ng. (2009). "Study of Propagation Loss Prediction in Forest Environment." Progress In Electromagnetics Research B 17: 117–33. doi:10.2528/PIERB09071901.

Mokhtari, H., and P. Lazaridis. (1999). "Comparative Study of Lateral Profile Knife-Edge Diffraction and Ray Tracing Technique Using GTD in Urban Environment."

IEEE Transactions on Vehicular Technology 48 (1): 255–61. doi:10.1109/25.740101.

Okamoto, H., K. Kitao, and S. Ichitsubo. (2009). "Outdoor-to-Indoor Propagation Loss Prediction in 800-MHz to 8-GHz Band for an Urban Area." IEEE Transactions on Vehicular Technology 58 (3): 1059–67. doi:10.1109/TVT.2008.927996.

R, Mardeni, and T. Siva Priya. (2010). "Optimised COST-231 Hata Models for WiMAX Path Loss Prediction in Suburban and Open Urban Environments." Modern Applied Science 4 (9): 75. doi:10.5539/mas.v4n9p75.

Rappaport, T. S., S. Sun, R. Mayzus, H. Zhao, Y. Azar, K. Wang, G. N. Wong, J. K. Schulz, M. Samimi, and F. Gutierrez. (2013). "Millimeter Wave Mobile Communications for 5G Cellular: It Will Work!" IEEE Access 1: 335–49. doi:10.1109/ACCESS.2013.2260813.

Shabbir, Noman, et al. "Comparison of radio propagation models for long term evolution (Lte) network." arXiv preprint arXiv:1110.1519 (2011).

Sarkar. T., Ji. Z., Kim. K., Medourr. A. & Salazar- Palma. M. (2003). A Survey of Various Propagation Models for Mobile Communication. *IEEE Antennas and propagation magazine* 45: 3.

Sati. G., Singh. S. (2014). A Review on outdoor Propagation models in Radio Communication. *Computer Engineering & Science* 4: 64-68.

Wei, Hung-Yu, S. Ganguly, R. Izmailov, and Z. J. Haas. (2005). "Interference-Aware IEEE 802.16 WiMax Mesh Networks." In 2005 IEEE 61st Vehicular Technology Conference, 5:3102–3106 Vol. 5. doi:10.1109/VETECS.2005.1543918.

Z, Nadir, Elfadhil N, and Touati F. (2008). "Pathloss Determination Using Okumura-Hata Model and Spline Interpolation for Missing Data for Oman." ResearchGate 2170 (1). https://www.researchgate.net/publication/44261983_Pathloss_Determination_using_Okumura-Hata Model and Spline Interpolation for missing_Data_for_Oman.

Yi. H. (2013). Outdoor Sfrength Measurement at TV band and ISM band in Otaniemi campus.

Yih-Guang. J., Yang-Han. L., Hsien-Wei. T., Ming Hsueh. C., Jheng.Y. L. & Chih-Weisu. (2007). Comparison of propagation path loss models. *IEEE-C802.16m-07/121*, call for comments.

Zhang, Yan. (2009). WiMAX Network Planning and Optimization. CRC Press.